VANDERBILT UNIVERSITY


Physics-Constrained Learning of PDE Systems with Uncertainty Quantified Port-Hamiltonian Models

Kaiyuan Tan, Peilun (Tommy) Li, Thomas Beckers

Department of Computer Science, Vanderbilt University, USA

16th World Congress on Computational Mechanics and 4th Pan American Congress on Computational Mechanics

Motivation



[Bending drill string on oil rig [zhang et al]]



[Festo]

Modeling PDE systems is challenging due to high complexity

Need for expressive, reliable, well-generalizing, and flexible models


Problem Statement

(partially) unknown function

PDE system

$$0 = f(x, \frac{\partial x}{\partial t}, \frac{\partial x}{\partial z}, \ldots)$$

+ known boundary conditions



Dataset

$$\mathcal{D} = \{(t_1, z_1, x(t_1, z_1), u(t_1)), \ldots, (t_{N_t}, z_{N_z}, x(t_{N_t}, z_{N_z}), u(t_{N_t}))\}$$

Need a model that

- represents a large class of systems -> Expressive
- allows uncertainty quantification -> Reliable
- consistent with physics -> Generalizes well
- Requires minimal expert knowledge -> Flexible

Related Work

	Generalizability	Uncertainty Quantification	Minimal Expert Knowledge	Expressive
Physics based models	✓	✓		✓
Pure, Data-Driven Methods (NN, GPs…)		✓	✓	
Physics-Informed Neural Networks (PINNs)	✓	✓		✓
GP-dPHS (This work)	✓	✓	✓	✓

Distributed Port-Hamiltonian systems + Gaussian Processes


Physics Model

Ports, Dissipation

Hamiltonian → port-Hamiltonian System

PDE

→ Distributed port-Hamiltonian System



Interconnection

Dissipation

Hamiltonian

$$\frac{\partial x}{\partial t}(t,z) = (J - R)\delta_x \mathscr{H} + Gu$$

Input

$$y = G\delta_x \mathscr{H}$$

$$w = B_{\mathscr{Z}}(\delta_x \mathscr{H}, u)$$

Output

Boundary Condition

- Skew-adjoint constant differential operator J ensures energy conservation
- R is a constant differential operator that defines dissipation

Extension to PDEs

	ODE model	PDE model
Dynamics	$\dot{x}(t) = [J(x) - R(x)]\frac{\partial H}{\partial x} + G(x)u$	$\frac{\partial x}{\partial t}(t,z) = [J - R]\delta_x \mathscr{H} + Gu$ $w = B_{\mathscr{Z}}(\delta_x \mathscr{H}, u)$
Energy	$H(x)$	$\mathscr{H}(x) = \int_{\mathscr{Z}} H(z,x)dV$
Interconnection	Skew-symmetric $J(x)$	Matrix differential operator J
Training data	$\mathscr{D} = \{t_i, x(t_i), u(t_i)\}_{i=0}^{i=N_t-1}$	$\mathscr{D} = \{t_i, z_j, x(t_i,z_j), u(t_i)\}_{i=j=0}^{i=N_t-1,j=N_z-1}$
Output	Samples of state over time	Samples of state over time and spatial

dPHS example

Vibration of a string with nonlinear stress-strain curve


$$\frac{\partial^2 x}{\partial t^2} - f\left(\frac{\partial x}{\partial z}\right)\frac{\partial^2 x}{\partial z^2} = 0,$$

In dPHS form

$$\frac{\partial}{\partial t}\begin{bmatrix} p(t,z) \\ q(t,z) \end{bmatrix} = \underbrace{\begin{bmatrix} 0 & \frac{\partial}{\partial z} \\ \frac{\partial}{\partial z} & 0 \end{bmatrix}}_{J-R} \delta_{pq}\mathscr{H}(p,q)$$

$\frac{\partial x}{\partial t}$ (↓ to $p(t,z)$)

$\frac{\partial x}{\partial z}$ (↑ to $q(t,z)$)



Example ground truth Hamiltonian functional

$$\mathscr{H} = \int_Z \int s(q)q(t,z)dq + p(t,z)^2 dz$$

Gaussian process


Prior: Gaussian distribution over function space

$$f(x) \sim GP(m(x), k(x, x'))$$

Mean function

Covariance

$$\text{posterior} = \frac{\text{likelihood} \times \text{prior}}{\text{marginal likelihood}}$$



Gaussian process


Prior: Gaussian distribution over function space

$$f(x) \sim GP(m(x), k(x, x'))$$

Mean function

Covariance

$$\text{posterior} = \frac{\text{likelihood} \times \text{prior}}{\text{marginal likelihood}}$$



Posterior

$$\mu(y^* \mid x^*, \mathscr{D}) = k(x^*, X)[K(X, X) + \sigma^2 I]^{-1} Y$$

$$\Sigma(y^* \mid x^*, \mathscr{D}) = k(x^*, x^*) - k(x^*, X)[K(X, X) + \sigma^2 I]^{-1} k(x^*, X)^\top$$

C.E. Rasmussen. Gaussian Processes for Machine Learning. 2006

Gaussian process


Prior: Gaussian distribution over function space

$$f(x) \sim GP(m(x), k(x, x'))$$

Mean function

Covariance

$$\text{posterior} = \frac{\text{likelihood} \times \text{prior}}{\text{marginal likelihood}}$$




Closed under linear operators

$$f(x) = \mathscr{G}_x g(x) \sim GP(\mathscr{G}_x \mu_g, \mathscr{G}_x k_g \mathscr{G}_x^\top)$$


C.E. Rasmussen. Gaussian Processes for Machine Learning. 2006

GP-dPHS




- **Idea:** encode the distributed Port-Hamiltonian system form into a GP function
- GP-dPHS includes all possible dPHS under the GP prior on Hamiltonian

GP-dPHS



$\hat{J}_\Theta$
$\hat{R}_\Theta$
$\hat{G}_\Theta$
GP-dPHS
Filter
$(t, x) \mapsto (x, \dot{x})$
State
Temporal
Spatial
System
dPHS
Approximation of Hamiltonian
Samples
PDE Solver
State
Temporal
Spatial
Model

Data Generation



- Use GP regression based on raw data
- Upsample data points from GP
- Take time derivative to obtain training data

GP-dPHS


$\hat{J}_\Theta$
$\hat{R}_\Theta$
$\hat{G}_\Theta$
GP-dPHS
Filter
$(t, x) \mapsto (x, \dot{x})$
State
Temporal
Spatial
System
dPHS
Approximation of Hamiltonian
Samples
PDE Solver
State
Temporal
Spatial
Model

Training

GP prior on Hamiltonian

$$\frac{\partial x}{\partial t} = [\hat{J}_\Theta - \hat{R}_\Theta]\delta_x \hat{\mathcal{H}} + \hat{G}_\Theta u \longrightarrow \dot{x} \sim GP(\hat{G}_\Theta u, k_{dphs}(x, x'))$$


Linear operator

Port-Hamiltonian Kernel

$$k_{dphs}(x, x') = \sigma_f^2(\hat{J}_\Theta - \hat{R}_\Theta)\delta_x \exp\underbrace{\left(-\frac{||x - x'||^2}{2\varphi_l^2}\right)}_{\text{Squared exp. kernel}} \overbrace{\delta_{x'}^\top(\hat{J}_\Theta - \hat{R}_\Theta)^\top}^{\text{Parametrized estimates}}.$$

Optimizing parameters by means of negative log marginal likelihood function

GP-dPHS


$\hat{J}_\Theta$
$\hat{R}_\Theta$
$\hat{G}_\Theta$
GP-dPHS
Filter
$(t, x) \mapsto (x, \dot{x})$
State
Temporal
Spatial
System
dPHS
Approximation of Hamiltonian
Samples
PDE Solver
State
Temporal
Spatial
Model

3. Prediction

dPHS

$$\begin{bmatrix} \dot{X} \\ \hat{f}(x^*) \end{bmatrix} = \mathcal{N}\left(0, \begin{bmatrix} K_{dphs} & k_{dphs}(X, x^*) \\ k_{dphs}(X, x^*)^\top & k_{dphs}(x^*, x^*) \end{bmatrix}\right) \qquad \dot{x} = \hat{f}(x, \omega)$$

Not callable
(computational expensive)

Approximation of Hamiltonian

$$\begin{bmatrix} \dot{X} \\ \hat{\mathscr{H}}(x^*) \end{bmatrix} = \mathcal{N}\left(0, \begin{bmatrix} K_{dphs} & k_{\dot{x}\mathscr{H}}(X, x^*) \\ k_{\dot{x}\mathscr{H}}(X, x^*)^\top & k_{\mathscr{H}\mathscr{H}}(x^*, x^*) \end{bmatrix}\right) \qquad \hat{\mathscr{H}}(x^*, \omega) \xrightarrow{\text{Approx.}} \hat{\mathscr{H}}^*(x^*)$$

PDE Solver

$$\dot{x} = [\hat{J}_\Theta - \hat{R}_\Theta]\delta_x \hat{\mathscr{H}}^* + \hat{G}_\Theta u \xrightarrow{\text{Solver}} x(t, z)$$

Approximation of H: Callable and structure preserving


GP-dPHS example


Vibration of a string with
nonlinear stress-strain curve

$$\frac{\partial}{\partial t}\begin{bmatrix} p(t,z) \\ q(t,z) \end{bmatrix} = \underbrace{\begin{bmatrix} 0 & \frac{\partial}{\partial z} \\ \frac{\partial}{\partial z} & 0 \end{bmatrix}}_{J-R} \delta_{pq}\mathscr{H}(p,q)$$


$\frac{\partial x}{\partial t}$ (red arrow down to $p(t,z)$)


$\frac{\partial x}{\partial z}$ (red arrow up to $q(t,z)$)





GP-dPHS example






- True $\delta_q \mathscr{H}$ is within the quantified upper and lower bounds
- More data leads to less mean absolute error (MAE)

Conclusion

Gaussian Process + Distributed Port-Hamiltonian System



- Physics-constrained data-driven model for PDE systems
- Expressive and generalizable model for nonlinear systems
- Probabilistic nature enables uncertainty quantification

Contact Info: kaiyuan.tan@vanderbilt.edu

Website: www.tbeckers.com

K. Tan, P. Li, and T. Beckers, Physics-Constrained Learning for PDE Systems with Uncertainty Quantified Port-Hamiltonian Models. L4DC, 2024